


# HARDWARE AND INSTALLATION INSTRUCTIONS FOR ELEMENTS TORCHES

*The only products that come with hardware are the Elements torches (all 3 sizes) and the two torch accessories: the auger and the free standing base plate.*

## HARDWARE AND USES

Each Elements torch is shipped with:

- (1) Universal U-Bracket
- (4) 1/2" long 1/4-20 zinc Phillips flat head screws



Universal U-Bracket



1/2" long 1/4-20 zinc Phillips flat head screws (x4)

## UNIVERSAL U-BRACKET

The Universal U-Bracket can mount to any hard surface such as a wood deck or cement patio.

*Please note: once installed, the torch cannot be moved without disassembly.*

To mount the Universal U-Bracket:

1. Screw through the four predrilled holes at the base of the U-Bracket and into your surface (fig. 1).
2. Slide the torch over the Universal U-Bracket (fig. 2).
3. Attach the torch to the U-Bracket by screwing the four 1/2" long 1/4-20 zinc Phillips flat head screws into the predrilled holes on the sides of the torch (fig.3).

figure 1




figure 2





figure 3



# HARDWARE AND INSTALLATION

## INSTRUCTIONS FOR ELEMENTS TORCHES

*The only products that come with hardware are the Elements torches (all 3 sizes) and the two torch accessories: the auger and the free standing base plate.*

### AUGER AND FREE-STANDING BASE PLATE INSTALLATION

#### AUGER

*This is the accessory to choose if you want to mount your torch in the ground.* First, place the Universal U-Bracket on top of the Auger and secure with a 3/8 x 1" hex head zinc bolt (fig. 1). Next, use the hammer (fig.2) and the tturn bar (fig. 3) that comes with the auger to screw the Auger into the soil until the U-Bracket is level with the soil surface. Finally, attach the torch to the U-Bracket using the instructions for mounting the Universal U-Bracket (fig. 4 and 5)

*\*A video installation guide is available on our website at [www.northcape.com/northcape-fire/elements/](http://www.northcape.com/northcape-fire/elements/)*

figure 1




figure 2




figure 3




figure 4





figure 5



#### FREE-STANDING BASE PLATE

*This is the accessory to choose if you want to move your torch from place to place* The Free-Standing Base Plate provides a base for a single torch, without having to permanently install the torch on a hard surface. Mount the Universal U-Bracket to the Free-Standing Base Plate by first inserting an appropriately-sized screw through the predrilled hole going from the bottom side to the top (figure 1). Next, place the Universal U-Bracket over the screw (fig. 2) and use a flat zinc washer and a 3/8 zinc hex nut to secure the U-Bracket to the Base Plate (fig. 3). Make sure to snugly tighten the hex nut. Once the Universal U-Bracket has been mounted to the Free-Standing Base Plate, attach the torch to the U-Bracket using the instructions for mounting the Universal U-Bracket (fig. 4 and 5).

figure 1




figure 2




figure 3




figure 4




figure 5

